




# Dell Vostro 3300 Memory Module Replacement

Written By: Johnathan Hammond



---

## INTRODUCTION

In this guide, we will show you how to remove and replace the Memory Module.



### TOOLS:

- [Phillips #0 Screwdriver](#) (1)
-

## Step 1 — Sliding the Latch



- Slide the battery release latch to the unlock position.

## Step 2 — Sliding the Latch



- Slide the other battery release latch to the unlock position.

### Step 3 — Slide the Battery



- Slide the battery and remove it from the computer.


### Step 4 — Base Cover



- Remove the screws that secure the base cover to the computer.




## Step 5 — Lifting the Base Cover




- Lift up the base cover and remove it from the computer.

## Step 6 — Releasing the Memory Module.



- Push apart the memory retention clips to release the memory module.

## Step 7 — Releasing the Memory Module



- Remove the memory module from its connector on the system board.