




# MSI GE62 Apache Pro 004 Motherboard Replacement

This guide will help you replace your motherboard in your MSI GE62 Apache Pro 004 device.

Written By: Alexander



---

## INTRODUCTION

This guide will show how to replace the motherboard on the MSI Apache Pro 004 laptop.

---

### TOOLS:


- [Phillips #00 Screwdriver](#) (1)
-

## Step 1 — Battery






- Start with the bottom of the laptop facing up.

## Step 2



- Remove the 15 screws from the bottom of the laptop with a PH1 screwdriver.
- Remove the bottom plate
- ⓘ Keep track of all the screws and which slot they came from, as they slightly differ. We recommend this system: lay out on a piece of paper and pretending the paper is the device. Place the screws on the paper approximately where they would go



## Step 3



- Remove the screw holding down the battery with a PH1 screwdriver.
- Pull out the battery.






## Step 4 — Motherboard



- Remove the cooling assembly by unscrewing the fourteen screws holding it in place.

## Step 5



- Remove the speakers holding the motherboard in place, located on the bottom left and bottom right of the device.
- Unfasten the 8 screws holding the motherboard in place.
- Pull out the motherboard.

To reassemble your device, follow these instructions in reverse order.